# SR Field-Adjustable Strip Light



## Field-Adjustable Strip Light









#### **PROJECT:**

DATE:

TYPE:

#### PREPARED BY:







## **KEY FEATURES**

- Available models with selectable wattages:
  - 2 Ft: (19/14/10W)
  - 4 Ft: (40/30/20W)
  - 8 Ft: (60/50/40W)
- Field-adjustable CCT: 5000/4000/3500K
- Available with smart controls
- Standard J-Box adapter. V-hooks are optional accessory for suspended mounting and Joiner Kit avaiable for daisy chain use.
- UL Listed for damp locations
- 0-10V dimming
- 5-Year, limited warranty

## **TECHNICAL SPECIFICATIONS**

## COMPLIANCE

## **UL Listed**

Suitable for damp locations

## IESNA LM-79 & LM-80 Testing

RAB LED luminaires and LED components have been tested by an independent laboratory in accordance with IESNA LM-79 and LM-80  $\,$ 

#### **DLC Listed**

This product is on the Design Lights Consortium (DLC) Qualified Products List and is eligible for rebates from DLC Member Utilities. Designed to meet DLC 5.1 requirements.

CATALOG#	DLC ID
SR2	S-BY8SM3
SR4	S-CDUVBW
SR8	S-FP3EWO

## LED CHARACTERISTICS

#### **LEDs**

Long-life, high-efficacy, discrete, surface-mount LEDs

#### **Color Consistency**

4-step MacAdam Ellipse binning to achieve consistent fixture-to-fixture color

#### **Color Uniformity**

RAB's range of Correlated Color Temperature follows the guidelines of the American National Standard for Specifications for the Chromaticity of Solid State Lighting (SSL) Products, ANSI C78.377-2017.

### **CONSTRUCTION**

#### **Cold Weather Starting**

The minimum starting temperature is -20°C (-4°F)

## Cold Weather Starting for battery back-up

The minimum starting temperature is 0°C (32°F)

## **Maximum Ambient Temperature**

Suitable for use in up to 50°C (122°F)

## Maximum Ambient Temperature for battery back-up

SR2: Suitable for use in up to 50°C (122°F) SR4/SR8: Suitable for use in up to 60°C (140°F)

## Mounting

Surface mounting standard. V-Hooks and Chain mounting available (ordered separately, SR VHOOK KIT).

#### Housing

Iron

## Lens

Polycarbonate

#### Finish

Formulated for high durability and long-lasting color

#### **Green Technology**

Mercury and UV free. RoHs-compliant components.

## SR Field-Adjustable Strip Light

## **TECHNICAL SPECIFICATIONS**

## **ELECTRICAL**

#### **Drivers:**

Constant Current, Class 2, Class P, 120-277V, 50/60 Hz, SR2 19W: 120V: 0.09A, 208V: 0.09A, 240V: 0.08A, 277V: 0.07A SR2 14W: 120V: 0.12A, 208V: 0.07A, 240V: 0.06A, 277V: 0.05A SR2 10W: 120V: 0.08A, 208V: 0.05A, 240V: 0.04A, 277V: 0.04A SR4 40W: 120V: 0.33A, 208V: 0.19A, 240V: 0.17A, 277V: 0.14A SR4 30W: 120V: 0.25A, 208V: 0.14A, 240V: 0.13A, 277V: 0.11A SR4 20W: 120V: 0.17A, 208V: 0.10A, 240V: 0.08A, 277V: 0.07A SR8 60W: 120V: 0.50A, 208V: 0.29A, 240V: 0.25A, 277V: 0.22A SR8 50W: 120V: 0.42A, 208V: 0.24A, 240V: 0.21A, 277V: 0.18A SR8 40W: 120V: 0.33A, 208V: 0.19A, 240V: 0.17A, 277V: 0.14A

#### **Dimming Driver:**

Driver includes dimming control wiring for 0-10V dimming systems. Requires separate 0-10V DC dimming circuit. Dims down to 10%.

#### THD:

SR2: 6.33% at 120V, 12.02% at 277V SR4: 6.22% at 120V, 14.88% at 277V SR8:7.52% at 120V, 7.96% at 277V

#### **Power Factor:**

SR2: 99.8% at 120V, 98.22% at 277V SR4: 99.79% at 120V, 98.26% at 277V SR8: 99.38% at 120V, 94.72% at 277V

#### **Surge Protection**

1kV + 2kV

## **ELECTRICAL (CONTINUED)**

#### **Battery Backup Light Loss Factor:**

SR2:

19W: 0.0223 14W: 0.0276 10W: 0.042 SR4:

40W: 0.0243 30W: 0.032 20W: 0.0454 SR8:

60W: 0.0171 50W: 0.02 40W: 0.0247

Note: All values are typical (tolerance +/- 10%)

#### **OTHER**


### **Buy American Act Compliance:**

RAB values USA manufacturing! Upon request, RAB may be able to manufacture this product to be compliant with the BUY American Act (BAA). Please contact customer service to request a quote for the product to be made BAA compliant.

#### Warranty

The RAB 5-year, limited warranty covers light output, driver performance and paint finish. RAB's warranty is subject to all terms and conditions found at rablighting.com/warranty.

### **DIMENSIONS**



MODEL#	A	B (with PIR sensor)	С	D	Weight (Lbs)
SR2	24"	26 7/8"	3 7/8"	2 3/8"	2.5
SR4	47 1/4"	50 1/16"	3 7/8"	2 3/8"	4.5
SR8	94 1/2"	97 5/16"	3 7/8"	2 3/8"	8.5

ACCESSORI	ES		
IMAGE	SKU#	UPC	DESCRIPTION
	SR VHOOK KIT	192552004206	SR VHOOK MOUNT KIT 2-40" CHAIN, ANCHOR, SCREWS
	SR JOIN KIT	192552004190	SR END JOIN KIT WITH BRACKET/NUTS/WIRE/ANCHOR

# SR Field-Adjustable Strip Light

	P	ER	FC	RI	ИА	NCE
--	---	----	----	----	----	-----

SR2	5000K	4000K	3500K	5000K	4000K	3500K	5000K	4000K	3500K
WATTAGE		19W			14W		10W		
INPUT WATTS	20.6W	19.9W	20.5W	14.6W	14.4W	14.6W	10.2W	10W	10.3W
LUMENS	2995	2998	2887	2189	2224	2115	1590	1606	1552
EFFICACY (LM/W)	145.5	150	140.6	149.9	154.5	144.8	155.9	160.6	150.6
CRI	83	84	84	83	84	84	83	85	84
VOLTAGE RATINGS	120-277V								

SR4	5000K	4000K	3500K	5000K	4000K	3500K	5000K	4000K	3500K
WATTAGE		40W			30W 20W				
INPUT WATTS	42.6W	40.8W	42.6W	31.6W	30.5W	31.7W	20.7W	20.1W	20.8W
LUMENS	6155	6174	5976	4702	4754	4579	3234	3289	3155
EFFICACY (LM/W)	144.5	151.3	140.2	148.8	155.9	144.5	156.2	163.7	151.7
CRI	83	84	84	83	84	84	83	84	84
VOLTAGE RATINGS	E RATINGS 120-277V								

SR8	5000K	4000K	3500K	5000K	4000K	3500K	5000K	4000K	3500K
WATTAGE		60W 50W					40W		
INPUT WATTS	60.6W	59.4W	60.7W	50W	49.9W	50W	40.2W	39.9W	40.1W
LUMENS	8690	8986	8518	7383	7761	7153	6053	6328	5855
EFFICACY (LM/W)	143.4	150.9	140.2	147.78	155.4	143.1	150.6	158.5	145.9
CRI	83	85	84	83	85	84	83	85	84
VOLTAGE RATINGS 120-277V									

## ORDERING MATRIX

## SR Field-Adjustable Strip Light

Family	S	ize/Wattages	Мо	ounting	Color	Temperature	Fin	ish		Voltage		Options
SR												
	2	2 Feet (19/14/10W)	BLANK	J-Box Adaptor	BLANK	5000/4000/3500	BLANK	White	BLANK	120-277V,	BLANK	No Option
	4	4 Feet (40/30/20W)								0-10V Dimming	/E	Battery Back Up
	8	8 Feet (60/50/40W)								_	/MVS	Microwave Occupancy Sensor
											/PIR	Passive Infrared Occupancy Sensor
											/LCBS	Lightcloud Blue PIR Sensor
											/LCBS/MVS	Lightcloud Blue MVS Sensor
											/MVS/E	Microwave Occupancy Sensor
												/Battery Back Up
											/PIR/E	Passive Infrared Occupancy Sensor
												/Battery Back Up
											/LCBS/E	Lightcloud Blue PIR Sensor
												/Battery Back Up
											/LCBS/MVS/E	5
												/Battery Back Up